

30° ADAPTOR <u>-30°</u>



© 2009 Tyco Electronics Corporation. All ri						
Tyco Electronics Raychem Adapter 305 Constitution Drive Menlo Park, CA 94025, USA			TITLE: HexaShield Adaptor 30 Deg. for Code 40 Connectors Plain Clamping Nut			
DIMENSIONS ARE IN MILLIMETERS. at an		Tyco Electronics reserves the ri at any time. Users should evalu product for their application.		DOCUMENT NO. HEX40-KC-30-YY	′-AYY-1-Y	Y
DRAWN: A. BUI	APPROVED: M. PIOZET	DATE: JAN 19, 2009	Cage Code: 06090	FILE: HEX40-KC-30-YY-AYY-1-YY.doc	SCALE: NONE	SHEET: 1 OF 4
	•	·	f this document is prin	tad it basemas uncentrelled. Check for t	he latest revisio	

If this document is printed it becomes uncontrolled. Check for the latest revision.

 REV:
 ECO-09 DATE:

 A
 002052
 JAN 26, 2009

### KIT DESCRIPTION

ITEM	DESCRIPTION	MATERIAL
1	BODY ASSEMBLY	NUT – STAINLESS STEEL
		BODY – STAINLESS STEEL
2	CLAMPING NUT - PLAIN	STAINLESS STEEL
3	CONIC RING	STAINLESS STEEL
4	STAR - PLAIN	STAINLESS STEEL

#### TABLE OF DIMENSIONS

Order Number	Shel	Size	ØA Thread Class 6H	<b>ØВ</b> Мах	ØC Max	D Max	E Max	Ferrule Quantity	
	Mil.	Com.	01000 011	Max	Max	Max	Max	Std.	Optional
09	A	09	M12 x 1	19.0 [0.75"]	17.5 [0.69"]	11.5 [0.45"]	24.0 [0.94"]	1	-
11	В	11	M15 x 1	22.0 [0.87"]	21.5 [0.85"]	12.0 [0.47"]	24.5 [0.96"]	2	-
13	С	13	M18 x 1	25.5 [1.00"]	22.5 [0.89"]	12.5 [0.49"]	25.0 [0.98"]	3	-
15	D	15	M22 x 1	30.5 [1.20"]	25.5 [1.00"]	13.0 [0.51"]	25.5 [1.00"]	5	-
17	E	17	M25 x 1	33.5 [1.32"]	28.5 [1.12"]	13.5 [0.53"]	26.0 [1.02"]	6	7
19	F	19	M28 x 1	37.0 [1.46"]	31.5 [1.24"]	14.0 [0.55"]	26.5 [1.04"]	7	-
21	G	21	M31 x 1	38.5 [1.52"]	35.0 [1.38"]	14.5 [0.57"]	27.0 [1.06"]	9	11
23	Н	23	M34 x 1	42.0 [1.65"]	38.0 [1.50"]	15.0 [0.59"]	27.5 [1.08"]	10	11, 12 13, 15
25	J	25	M37 x 1	46.5 [1.83"]	41.0 [1.61"]	15.5 [0.61"]	28.0 [1.10"]	12	13, 14, 15, 17, 18

### PART NUMBERING

- CONNECTOR CODE NUMBER HEX40 =-MIL-C-38999 SERIES III AND IV - MATERIAL CODE:	HEX40-KC-30-21-A9-1-DS
K = STAINLESS STEEL - PLATING CODE:	
C = ELECTROLESS NICKEL TO SAE-AMS-C-26074 - BODY STYLE	
30 = 30° - ORDER NUMBER	
- 1 = PLAIN CLAMPING NUT - DS = DRILLED STAR - OPTIONAL - SEE NOTE 2	

				© 2009 Tyco Electronics Cor	poration. All ri	ights reserved	
Tyco Electronics Raychem Adapter 305 Constitution Drive Menio Park, CA 94025, USA				HexaShield Adaptor 30 Deg. for Code 40 Connectors Plain Clamping Nut			
UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN MILLIMETERS.		Tyco Electronics reserves the right to amend this drawing at any time. Users should evaluate the suitability of the		DOCUMENT NO.			
INCH DIMENSIONS ARE SHOWN IN BRACKETS		product for their application.		HEX40-KC-30-YY	′-AYY-1-Y	Y	
DRAWN: A. BUI	APPROVED: M. PIOZET	DATE: JAN 19, 2009	Cage Code: 06090	FILE: HEX40-KC-30-YY-AYY-1-YY.doc	SCALE: NONE	SHEET: 2 OF 4	
_	-	-,			1 1 2 2 1 2 2 2 2	-	

If this document is printed it becomes uncontrolled. Check for the latest revision.

#### **APPLICATION**

- These adaptors are designed to be mounted on the following connectors:

MIL-C-38999 Series III and IV

- They are qualified to the Raychem specification RB-114, when installed on metallic Mil-Specification circular connectors only.
- They are designed primarily for open wire bundle installation but are also designed to accept Raychem heat shrink moulded parts where strain relief is required - see illustration.



- Use in conjunction with ferrules HET-A-0XX, which are purchased separately. Refer to HET-A-0XX S.C.D. for relevant selection details.

#### INSTALLATION

- See Installation Procedure RPIP-696-04.

#### PACKAGING

All components are supplied in a plastic bag.

#### NOTES!

- 1. Item 4 Star is not supplied with Hexashield Order Number 09.
- 2. The DS option, illustrated below, is for a Drilled Star that is available on sizes 15 to 25 only. This option is to allow unshielded wires to pass through the assembly.





STAR SIZE	15	17	19	21	23	25
ØF MAX	3.0	6.0	9.0	12.0	15.0	18.0
	[0.12"]	[0.24"]	[0.35"]	[0.47"]	[0.59"]	[0.71"]

a studie in Companyation All sights as some of

3. Where the ferrule quantities required are standard, the item 4 - Star - is also standard.

Tyco Electronics Raychem Adapter 305 Constitution Drive Menio Park, CA 94025, USA			HexaShield Adapto Code 40 Con Plain Clampi	nectors	. for	
UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN MILLIMETERS. INCH DIMENSIONS ARE SHOWN IN BRACKETS		Tyco Electronics reserves the at any time. Users should eva product for their application.		DOCUMENT NO. HEX40-KC-30-YY	′-AYY-1-Y	Υ
DRAWN: A. BUI	APPROVED: M. PIOZET	DATE: JAN 19, 2009	Cage Code: 06090	FILE: HEX40-KC-30-YY-AYY-1-YY.doc	SCALE: NONE	SHEET: 3 OF 4
			If this document is prin	ted it becomes uncontrolled. Check for t	he latest revisi	on.

REV:	ECO-09-	DATE:
Α	002052	JAN 26, 2009

If the optional quantity is selected then 2 items 4 will be supplied - one "split" and the other one standard. See below for illustration. Note: Star combination may vary from Order Number to Order Number.

EXAMPLE: FERRULE QUANTITY CODE -A13

-A13 = -A10 SPLIT STAR + -A3 STANDARD STAR



4. Assembly is to be permanently marked with Code Identity Number and Part Number. (e.g. 06090 HEX40-KC-30-21-A9-1)

© 2009 Tyco Electronics Corporation. All rights reserve						
Tyco Electronics Raychem Adapter 305 Constitution Drive Menio Park, CA 94025, USA			HexaShield Adapto Code 40 Con Plain Clampi	nectors	for	
UNLESS OTHERWI DIMENSIONS ARE INCH DIMENSIONS BRACKETS	IN MILLIMETERS.	Tyco Electronics reserves the at any time. Users should eva product for their application.		DOCUMENT NO. HEX40-KC-30-YY		Y
DRAWN: A. BUI	APPROVED: M. PIOZET	DATE: JAN 19, 2009	Cage Code: 06090	FILE: HEX40-KC-30-YY-AYY-1-YY.doc	SCALE: NONE	SHEET: 4 OF 4
			If this document is prin	ted it becomes uncontrolled. Check for t	the latest revision	on.

f this document is printed it becomes uncontrolled. Check for the latest revision.